


PAVO P LED
Diffuser and Wall Luminaires



Images for the product family and options:



Table with 2 columns: Category (Description, General data, Installation, Environment, Application) and Details (Surface mounted LED luminaire, Light distribution: direct, Optical system: opal PMMA diffuser, Housing: steel, Colour: white, RAL 9003, Mains voltage: 220-240V, 50-60Hz, LED lifetime, h: 40000/L70B50, SDCM: 5, Protection class IEC: I, Ingress protection code: IP44, Mechanical impact resistance: IK02, Operating temperature range, °C: ta -15...+35, On the ceiling or wall. Screw terminal, 3x1.5mm2, Indoor, Office, education, hotel, corridor, staircase, healthcare, bathroom, public place).

Table with 11 columns: Product, Length, mm, Width, mm, Height, mm, Luminaire output*, lm, System power*, W, System efficacy*, lm/W, CRI * (Ra), CCT*, K, Weight, kg. Rows include various Pavo P LED models with different dimensions, outputs, and weights.

*Tolerance range for optical and electrical data: ±10%. Values apply to an ambient temperature of 25°C. NORTHCLIFFE LIGHTING is constantly developing and improving its products. The right is reserved to change any product specifications without prior notification
*Photos are for illustrational purposes only. The exact appearance of the product may vary depending on the monitor settings, options selected and other factors.

Available options:

T830	Colour temperature 3000K, CRI 80+
T840	Colour temperature 4000K, CRI 80+
DALI	Driver with DALI interface and switch-control dimming
COR	Driver with Corridor function (never off)
COR1min	Driver with Corridor function 1min (switch off after 1 min.)
COR30min	Driver with Corridor function 30min (switch off after 30 min.)
MW	Integrated microwave (MW) motion sensor with on-off control
MWRFMD	Built-in microwave motion sensor with integrated wireless transceiver. Sensor can serve as both master and slave. Functions: Staircase, Corridor, dimming control.
MWRFM	Built-in microwave motion sensor with integrated wireless transceiver. Sensor can serve as both master and slave. Functions: Staircase, Corridor.

MWRFSD	Built-in wireless receiver for receiving master luminaire control signals. Functions: Staircase, Corridor, dimming control.
MWRFs	Built-in wireless receiver for receiving master luminaire control signals. Functions: Staircase, Corridor.
EM3	Emergency version 3 hours
EM3B	Emergency version 3 hours (best available technology)
EM3A	Emergency version equipped with an autonomous testing system, 3 hours
EM3D	Emergency version 3 hours with DALI interface
<i>*note - Operating temperature range for Luminaires with EM option, C: ta 0...+35</i>	

